

FIRELINK 0,6/1

Fire resistant cable splice for power cables BFOU 0,6/1 kV



Description

Cable splicing concept based on flame retardant, Zero-halogen heat-shrinkable tubing.

Qualification

The concept is tested and approved in acc. with:

- IEC 60331-1 (Fire resistant)
- IEC 60332-1 (Flame retardant)
- IEC 61034-1 (Low smoke)
- EN 50393:2014 (Electrical type approval)

Test reports on request.

Special features

- Quick and easy installation
- Slim and limited diameter increase
- Each kit cover several cables
- Each kit includes appropriate connectors in acc. with DIN 46341-1 for 0,5-70 mm² and DIN 46267 for 25-300mm²

For selection table and product number, see next page.



SELECTION TABLE

Firelink 0,6/1

Cable size mm ²	Product name	Prod.no	Cable size mm ²	Product name	Prod.no
1x16	FIRELINK 0,6/1-1x16-35	11 316 82	4x1,5	FIRELINK 0,6/1-2/4x1,5-2,5	11 316 88
1x25	FIRELINK 0,6/1-1x16-35	11 316 82	4x2,5	FIRELINK 0,6/1-2/4x1,5-2,5	11 316 88
1x35	FIRELINK 0,6/1-1x16-35	11 316 82	4x4	FIRELINK 0,6/1-3/4x4-6	11 316 91
1x50	FIRELINK 0,6/1-1x50-95	11 316 83	4x6	FIRELINK 0,6/1-3/4x4-6	11 316 91
1x70	FIRELINK 0,6/1-1x50-95	11 316 83	4x10	FIRELINK 0,6/1-3/4x10-16	11 316 92
1x95	FIRELINK 0,6/1-1x50-95	11 316 83	4x16	FIRELINK 0,6/1-3/4x10-16	11 316 92
1x120	FIRELINK 0,6/1-1x120-150	11 316 84	4x25	FIRELINK 0,6/1-3/4x25-35	11 316 93
1x150	FIRELINK 0,6/1-1x120-150	11 316 84	4x35	FIRELINK 0,6/1-3/4x25-35	11 316 93
1x185	FIRELINK 0,6/1-1x185	11 316 85	4x50	FIRELINK 0,6/1-4x50-70	11 316 98
1x240	FIRELINK 0,6/1-1x240	11 316 86	4x70	FIRELINK 0,6/1-4x50-70	11 316 98
1x300	FIRELINK 0,6/1-1x300	11 316 87	4x95	FIRELINK 0,6/1-4x95-120	11 316 99
			4x120	FIRELINK 0,6/1-4x95-120	11 316 99
2x1,5	FIRELINK 0,6/1-2/4x1,5-2,5	11 316 88			
2x2,5	FIRELINK 0,6/1-2/4x1,5-2,5	11 316 88	7x1,5	FIRELINK 0,6/1-7x1,5-2,5	11 317 00
2x4	FIRELINK 0,6/1-2x4-6	11 316 89	7x2,5	FIRELINK 0,6/1-7x1,5-2,5	11 317 00
2x6	FIRELINK 0,6/1-2x4-6	11 316 89			
2x10	FIRELINK 0,6/1-2x10-16	11 316 90	12x1,5	FIRELINK 0,6/1-12x1,5-2,5	11 317 01
2x16	FIRELINK 0,6/1-2x10-16	11 316 90	12x2,5	FIRELINK 0,6/1-12x1,5-2,5	11 317 01
3x1,5	FIRELINK 0,6/1-2/4x1,5-2,5	11 316 88	19x1,5	FIRELINK 0,6/1-19x1,5-2,5	11 317 02
3x2,5	FIRELINK 0,6/1-2/4x1,5-2,5	11 316 88	19x2,5	FIRELINK 0,6/1-19x1,5-2,5	11 317 02
3x4	FIRELINK 0,6/1-3/4x4-6	11 316 91			
3x6	FIRELINK 0,6/1-3/4x4-6	11 316 91	27x1,5	FIRELINK 0,6/1-27x1,5-2,5	11 317 03
3x10	FIRELINK 0,6/1-3/4x10-16	11 316 92	27x2,5	FIRELINK 0,6/1-27x1,5-2,5	11 317 03
3x16	FIRELINK 0,6/1-3/4x10-16	11 316 92			
3x25	FIRELINK 0,6/1-3/4x25-35	11 316 93	37x1,5	FIRELINK 0,6/1-37x1,5-2,5	11 317 04
3x35	FIRELINK 0,6/1-3/4x25-35	11 316 93	37x2,5	FIRELINK 0,6/1-37x1,5-2,5	11 317 04
3x50	FIRELINK 0,6/1-3x50-70	11 316 94			
3x70	FIRELINK 0,6/1-3x50-70	11 316 94			
3x95	FIRELINK 0,6/1-3x95-120	11 316 95			
3x120	FIRELINK 0,6/1-3x95-120	11 316 95			
3x150+E	FIRELINK 0,6/1-3x150-185+E	11 316 96			
3x185+E	FIRELINK 0,6/1-3x150-185+E	11 316 96			
3x240+E	FIRELINK 0,6/1-3x240+E	11 316 97			